

<b>STANDARD FORMAT FOR ELECTRONIC CONTEST LOG EXCHANGE ( VIENNA 1998)</b>	Issue: 1,1
<b>Subject</b> Electronic Data Interchange - EDI-file format for contests in Region 1 above 30 MHz	
<b>Scope</b> This document is the specification for the Region 1 above 30 MHz contest file formats . Examples for commonly known contests are shown in the appendix.  The aim is to make contest-log programmers able to deliver a standard (file) format from their programs, to enable contest managers to receive log data through various types of digital communication systems e.g. diskettes, e-mail, etc; for electronic evaluation purposes.	
<b>Original</b> Prepared by: Bo Hansen, OZ1FDJ, Søren Pedersen, OZ1FTU	

**Format**

[REG1TEST;1]File identifier;file version  
 F TName=Contest name  
 TDate=Beginning;ending date of contest  
 PCall=Callsign used  
 PWWLo=WWL used  
 PExch=Exchange used  
 F PAdr1=Address line 1 from where the contest took place  
 F PAdr2=Address line 2 from where the contest took place  
 F PSect=Section in which station participates  
 PBand=Band used during the contest  
 PClub=Club station where points can be accumulated  
 F RName=Name of responsible operator  
 RCall=Callsign of responsible operator  
 F RAdr1=Address line 1 of responsible operator  
 F RAdr2=Address line 2 of responsible operator  
 F RPoCo=Postal code of responsible operator  
 F RCity=City of responsible operator  
 F RCoun=Country of responsible operator  
 F RPhon=Phone number of responsible operator  
 F RHBBBS=Home BBS of responsible operator  
 MOpe1=Multi operator line 1  
 MOpe2=Multi operator line 2  
 F STXEq=TX equipment  
 F SPowe=TX power [W]  
 F SRXEq=RX equipment  
 F SAnte=Antenna  
 F SAnth=Antenna height above ground level [m];height above sea level [m]  
 CQSOs=Claimed number of valid QSOs;Band multiplier  
 CQSOP=Claimed number of QSO-points  
 CWWLs=Claimed number of WWLs;Bonus per each new WWL;WWL multiplier  
 CWWLB=Claimed number of WWL bonus points  
 CExcS=Claimed number of Exchanges;Bonus per each new Exchange;Exchange multiplier  
 CExcB=Claimed number of Exchange bonus points  
 CDXCs=Claimed number of DXCCs;Bonus per each new DXCC;DXCC multiplier  
 CDXCB=Claimed number DXCC bonus  
 CToSc=Claimed total score  
 CODXC=Call;WWL;distanceBest DX contact  
 [Remarks]Remarks identifier  
 F Remarks lines  
 [QSORecords;Number of QSO records following]QSO records identifier;number of QSO records following  
 Date;Time;Call;Mode code;Sent-RST;Sent QSO number;Received-RST;Received QSO number;Received exchange;Received-WWL; QSO-Points;New-Exchange-(N);New-WWL-(N);New-DXCC-(N);Duplicate-QSO- (D)

## Explanation of keywords

Keywords are defined as the word in front of the actual argument. The keyword is separated from the argument with an equal sign (=).

### [REG1TEST;1]

REG1TEST;1 is the file identifier and the file version. It serves as indicator for which format and version is being used and where data begins.

### TName

Argument describes the name of the contest in which the station participated.

### TDate

Arguments describe the beginning and ending dates of the contest. Arguments are separated with a semicolon (;). Arguments are written as YYYYMMDD.

### PCall

Argument describes the callsign used during the contest.

### PWWLo

Argument describes own World Wide Locator (WWL, Maidenhead, Universal Locator) used during the contest. Maximum length is six characters.

### PExch

Argument describes own Exchange during the contest. This can be any type of information, e.g. Province, DOK, County, State, Power, Name. Maximum length is six characters.

### PAdr1

Argument describes the address of the QTH used during the contest, line 1.

### PAdr2

Argument describes the address of the QTH used during the contest, line 2.

### PSect

Argument describes in which section the station is participating. Synonyms to the meaning "section" are: class, category, group etc.

### PBand

Argument describe which band was used during the contest. Please note the bands and which frequency range they represent in the table below:

<i>Frequency</i>	=	<i>PBand</i>
50 - 54 MHz	=	50 MHz
70 - 70,5 MHz	=	70 MHz
144 - 148 MHz	=	145 MHz
430 - 440 MHz	=	435 MHz
1240 - 1300 MHz	=	1,3 GHz
2300 - 2450 MHz	=	2,3 GHz
3400 - 3600 MHz	=	3,4 GHz
5650 - 5850 MHz	=	5,7 GHz
10,0 - 10,5 GHz	=	10 GHz
24,0 - 24,25 GHz	=	24 GHz
47,0 - 47,2 GHz	=	47 GHz
75,5 - 81 GHz	=	76 GHz
120 - 120 GHz	=	120 GHz
142 - 148 GHz	=	144 GHz
241 - 250 GHz	=	248 GHz

### PClub

Argument describes the callsign of the radio club where operator(s) are member. Can be used if points are accumulated to the club etc.

### RName

Argument describes the given- and surname of the responsible operator.

**RCall** Argument describes the callsign of the responsible operator.

### Adr1

Argument describes the address of the responsible operator, line 1.

### RAdr2

Argument describes the address of the responsible operator, line 2.

### RPoCo

Argument describes the postal code of the responsible operator.

### RCity

Argument describes the city of the responsible operator.

### RCoun

Argument describes the country of the responsible operator.

### RPhon

Argument describes the telephone number of the responsible operator.

### RHBBS

Argument describes the Bulletin Board System or electronic mail address of the responsible operator.

### MOpe1

Arguments describe the operators participating in the contest, line 1. All arguments separated with a semicolon (;). Responsible operator is not needed in this argument.

### MOpe2

Arguments describe the operators participating in the contest, line 2. All arguments are separated with a semicolon (;). Responsible operator is not needed in this argument.

### STXEq

Argument describes the transmitting equipment used during the contest.

### SPowe

Argument describes the transmitting power used during the contest, unit is Watt.

### SRXEq

Argument describes the receiving equipment used during the contest.

### SAnte

Argument describes the antenna system used during the contest.

### SAnth

Arguments describe the antenna height above ground level and sea level, unit is meter. All arguments separated with a semicolon (;).

### CQSOs

Arguments describe the claimed number of valid QSOs and the band multiplier. All arguments are separated with a semicolon (;).

### CQSOP

Argument describes the claimed total number of QSO-points. The format does not specify that QSO-points can only be based upon distances.

### CWWLs

Arguments describe the claimed number of WWLs worked, the number of bonus points claimed for each new WWL and the WWL multiplier. All arguments are separated with a semicolon (;).

If no bonus points are claimed then bonus points per each new WWL are set to zero (0). If no multiplication is used for each new WWL the multiplier is set to one (1).

### CWWLB

Argument describes the claimed total number of WWL bonus points.

### CExcs

Arguments describe the claimed number of Exchanges worked, the number of bonus points claimed for each new Exchange and the Exchange multiplier. All arguments are separated with a semicolon (;).

If no bonus points are claimed then bonus points per each new Exchange are set to zero (0). If no multiplication is used for each new Exchange the multiplier is set to one (1).

**CExcB**

Argument describes the claimed total number of Exchange bonus points.

**CDXCs**

Arguments describe the claimed number of DXCCs worked, the number of bonus points claimed for each new DXCC and the DXCC multiplier. All arguments are separated with a semicolon (;).

If no bonus points are claimed then bonus points per each new DXCC are set to zero (0). If no multiplication is used for each new DXCC the multiplier is set to one (1).

**CDXCB**

Argument describes the claimed total number of DXCC bonus points.

**CToSc**

Argument describes the total claimed score. The format does not specify how the total score is calculated.

**CODXC**

Arguments describe the claimed ODX contact call, WWL and distance. All arguments are separated with a semicolon (;).

**[Remarks]**

The [Remarks] identifier is used to mark where the Remarks begins. All lines following, until [QSORecords;Number of QSO records following], are remarks. If no remarks are written identifier must still be present.

**Remarks lines**

Remarks lines are where the station may write comments to the test. The number of lines is variable. All lines in between [Remarks] and [QSORecords;Number of QSO records following] are remarks.

**[QSORecords;Number of QSO records following]**

The [QSORecords;Number of QSO records following] is the QSO record identifier used to mark where QSO records begins, and how many consecutive QSO records to follow.

**QSO record definition**

Date;Time;Call;Mode code;Sent-RST;Sent QSO number;Received RST;Received QSO number;Received Exchange;Received-WWL;QSO-Points;New-Exchange-(N);New-WWL-(N);New-DXCC-(N);Duplicate-QSO-(D)  
All arguments are separated with a semicolon (;).

All fields in the QSO record is written on the same line, and ending with ASCII characters 13 and 10 (CR LF).

<u>Field</u>	<u>Maximum length</u>
Date	= YYMMDD, 6
6 characters	
Time	= UTC, 4
characters, with leading zeros	
Call	= 3 to 14
characters	14
Mode code	= 0 or 1
character	1
Sent-RST	= 0 or 2 or 3
characters	3
Sent QSO number	= 0 or 3 or 4
characters, with leading zeros	4
Received-RST	= 0 or 2 or 3
characters	3
Received QSO number	= 0 or 3 or 4
characters, with leading zeros	4
Received Exchange	= 0 or 1 to 6
characters (see also PExch)	6
Received WWL	= 0 or 4 or 6
characters, World Wide Locator	6
QSO points	= 1 to 6
characters, including bandmultiplier	6
New-Exchange	= 0 or 1
character, "N" if QSO is a new exchange	1
New-WWL	= 0 or 1
character, "N" if QSO is a new WWL	1
New-DXCC	= 0 or 1
character, "N" if QSO is a new DXCC	1
Duplicate-QSO	= 0 or 1
character, "D" if contact is a duplicate QSO	1
	61
	+ field separators, 14
	75

**Mode code**

The mode code is used to show which modes were used for the QSO. Below is a list of the code with corresponding

modes.

<u>Mode code</u>	<u>TX mode</u>	<u>RX mode</u>
0	non of below	non of
below		
1	SSB	SSB
2	CW	CW
3	SSB	CW
4	CW	SSB
5	AM	AM
6	FM	FM
7	RTTY	RTTY
8	SSTV	SSTV
9	ATV	ATV

If the mode is not important it can be left blank, i.e. not stated in rules/invitation.

**Characters**

Used characters are in accordance with the 7-bit ASCII alphabet and only characters with the following decimal number are allowed 10, 13, 32-127.

**Line length**

If line length is already specified it must not be exceeded, other lines must not exceed a length of 75 characters. Length is limited due to Packet Radio transferral.

**F**

All lines, in the format description, with the "F" denote that entry is a *free format*. This means that any of the above characters in the 7-bit ASCII alphabet can be used.

All other entries are *forced format* and characters, as above, are in capital. All numbers in forced format are positive integers and non-exponential notation and entry can not be left empty, i.e. 0 (zero) or greater. All forced formats must be in accordance with SI-units (Système International).

**Separator (;)**

This separator semicolon (;) is written to separate multiple information on same line.

If the format is used for a contest which does not use some of the QSO exchanges, i.e. QSO no., WWL and Exchange, these fields are left blank. Proper interpretation must be ensured by manager program.

**Faulty QSOs**

A duplicate QSO is marked with a "D" in the Duplicate-QSO field, and the QSO-points field is set to 0 (zero). The format does not define when a QSO is a duplicate.

An incomplete QSO is written with the information received, and the QSO-points field is set to zero (0).

In case of a mistake, an error mark must be inserted in the Callsign field to keep a correct flow in the number of QSOs records. The error mark must be an "ERROR" and the other fields except Time and Sent QSO no., if used, can be left empty. In case the empty field is accumulated, e.g. QSO-points, it is set to 0 (zero).

**QSO numbers**

The format does not define in what order the QSO numbers must be listed. It is possible to use the format to submit logs for contests requiring consecutive numbers for all QSOs, even if they are on different bands.

**Missing information**

If a contest log program can not fill in all the information, the missing information can be left blank, except if information is needed for claiming/calculating scores, e.g. log program cannot identify WWLs, DXCCs etc. If the information is required for the scores this log program can not be used for this particular contest anyway.

The following section describes different EDI-files for various commonly known contest types.

**Region 1 Contest, standard type**

[REG1TEST;1]  
 TName=IARU Region 1, March contest VHF  
 TDate=19950304;19950305  
 PCall=OZ1FDJ  
 PWWLo=JO65FR  
 PExch=  
 PAdr1=Herlevgaardsvej 32 A, st. tv., DK-2730 Herlev  
 PAdr2=  
 PSect=Multi operator  
 PBand=144 MHz  
 PClub=OZ2AGR  
 RName=Bo Hansen  
 RCall=OZ1FDJ  
 RAdr1=Herlevgaardsvej 32 A, st. tv.  
 RAdr2=  
 RPoCo=DK-2730  
 RCity=Herlev  
 RCoun=DENMARK  
 RPhon=(+45) 42 91 53 98  
 RHBS=OZ6BBS  
 MOpe1=OZ1FTU  
 MOpe2=  
 STXEq=FT-225RD+MRF247  
 SPowe=90  
 SRXEq=FT-225RD+MuTek+BF981 1,5 dB NF  
 SAnte=9 elements OZ5HF  
 SAntH=14;41  
 CQSOS=24;1  
 CQSOP=11579  
 CWWLs=19;0;1  
 CWWLB=0  
 CExcS=0;0;1  
 CExcB=0  
 CDXCs=7;0;1  
 CDXCB=0  
 CToSc=11579  
 CODXC=OY9JD;IP62OA;1302

[Remarks]  
 Nice with the Aurora, made it possible to work more than usual in a 24 h contest. Nice to hear Jon (OY9JD) again, but, many stations calling so no time for chat. Besides the Aurora there was only little activity, as usual, in Scandinavia.

[QSORecords;26]  
 950304;1445;OZ9SIG;1;59;001;59;006;;JO65ER;6;;N;N;  
 950304;1446;DL5BBF;1;54;002;59;023;;JO42LT;396;;N;N;  
 950304;1449;OZ1HLB/P;1;59;003;59;015;;JO55US;48;;N;;  
 950304;1450;DL6FBL;1;53;004;51;092;;JO40XL;608;;N;;  
 950304;1454;DF0TAU;1;54;005;59;084;;JO40QO;606;;N;;  
 950304;1508;DJ3QP;1;55;006;59;095;;JO42FB;485;;N;;  
 950304;1510;DG5TR;1;53;007;53;006;;JO53QP;242;;N;;  
 950304;1519;DL0WU;1;55;008;53;108;;JO31OF;609;;N;;  
 950304;1528;DL3LAB;1;59;009;59;046;;JO44XS;191;;N;;  
 950304;1532;DL5XV;1;56;010;59;033;;JO53AO;283;;N;;  
 950304;1544;OZ8RY/A;1;56;011;57;010;;JO66HB;39;;N;;  
 950304;1553;OZ1AOO;1;59;012;59;001;;JO65FR;1;;N;;  
 950304;1603;ERROR;;;013;;N;;0;;N;;  
 950304;1618;DL0WX;1;53;014;52;174;;JO30FQ;688;;N;;  
 950304;1626;SM4HFI;2;53A;015;54A;019;;JP70TO;573;;N;N;  
 950304;1631;GM4YXI;2;57A;016;55A;015;;IO87WI;911;;N;N;  
 950304;1636;OH2AAQ;2;52A;017;59A;015;;KO29FX;851;;N;N;  
 950304;1640;OH2BNH;2;55A;018;57A;024;;KP20LG;891;;N;N;  
 950304;1641;LA2AB;1;59A;019;57A;027;;JO59FV;479;;N;N;  
 950304;1646;SM5BSZ;2;55A;020;57A;029;;JO89IJ;480;;N;N;  
 950304;1700;SK5BN;2;51A;021;55A;026;;JP80UE;585;;N;N;  
 950304;1720;DL9LBA;2;529;022;559;056;;JO44UP;213;;N;N;  
 950304;1730;SK6NP;2;559;023;539;029;;JO68MB;262;;N;N;  
 950304;1736;OH1MDR;2;52A;024;57A;023;;KP01VJ;830;;N;N;  
 950304;1739;OY9JD;2;51A;025;52A;011;;IP62OA;1302;;N;N;  
 950304;1826;OZ9SIG;1;59;026;59;006;;JO65ER;0;;N;N;

**AGCW DL VHF Contest (contest manager: DJ2QZ)**

[REG1TEST;1]  
 TName=AGCW contest 2 m  
 TDate=19950318;19950318  
 PCall=OZ1FDJ  
 PWWLo=JO65FR  
 PExch=C  
 PAdr1=Herlevgaardsvej 32 A, st. tv., DK-2730 Herlev  
 PAdr2=  
 PSect=C  
 PBand=144 MHz  
 PClub=OZ2AGR  
 RName=Bo Hansen  
 RCall=OZ1FDJ  
 RAdr1=Herlevgaardsvej 32 A, st. tv.  
 RAdr2=  
 RPoCo=DK-2730

RCity=Herlev  
 RCoun=DENMARK  
 RPhon=(+45) 42 91 53 98  
 RHBS=OZ6BBS  
 MOpe1=  
 MOpe2=  
 STXEq=FT-225RD+MRF247  
 SPowe=90  
 SRXEq=FT-225RD+MuTek+BF981 1,5 dB NF  
 SAnte=9 elements OZ5HF  
 SAntH=14;41  
 CQSOS=24;1  
 CQSOP=11579  
 CWWLs=19;500;1  
 CWWLB=9500  
 CExcS=3;0;1  
 CExcB=0  
 CDXCs=7;0;1  
 CDXCB=0  
 CToSc=11579  
 CODXC=OY9JD;IP62OA;1302  
 [Remarks]  
 Nice with the Aurora, made it possible to work more than usual. Nice to hear Jon (OY9JD) again, but, many stations calling so no time for chat. Besides the Aurora there was only little activity, as usual, in Scandinavia.  
 [QSORecords;26]  
 950318;1600;OZ9SIG;2;599;001;599;006;B;JO65ER;6;N;N;N;  
 950318;1602;DL5BBF;2;549;002;599;023;C;JO42LT;396;N;N;N;  
 950318;1607;OZ1HLB/P;2;599;003;599;015;C;JO55US;48;N;;N;  
 950318;1609;DL6FBL;2;539;004;519;092;C;JO40XL;608;N;;N;  
 950318;1614;DF0TAU;2;549;005;599;084;B;JO40QO;606;N;;N;  
 950318;1618;DJ3QP;2;559;006;599;095;C;JO42FB;485;N;;N;  
 950318;1625;DG5TR;2;539;007;539;006;A;JO53QP;242;N;N;N;  
 950318;1628;DL0WU;2;559;008;539;108;C;JO31OF;609;N;N;N;  
 950318;1630;DL3LAB;2;599;009;599;046;C;JO44XS;191;N;N;N;  
 950318;1632;DL5XV;2;569;010;599;033;C;JO53AO;283;N;N;N;  
 950318;1644;OZ8RY/A;2;569;011;579;010;A;JO66HB;39;N;N;N;  
 950318;1653;OZ1AOO;2;599;012;599;001;A;JO65FR;1;N;N;N;  
 950318;1703;ERROR;;;013;;N;;0;;N;;  
 950318;1718;DL0WX;2;539;014;529;174;C;JO30FQ;688;N;N;N;  
 950318;1726;SM4HFI;2;53A;015;54A;019;C;JP70TO;573;N;N;N;  
 950318;1731;GM4YXI;2;57A;016;55A;015;C;IO87WI;911;N;N;N;  
 950318;1736;OH2AAQ;2;52A;017;59A;015;C;KO29FX;851;N;N;N;  
 950318;1740;OH2BNH;2;55A;018;57A;024;C;KP20LG;891;N;N;N;  
 950318;1741;LA2AB;2;59A;019;57A;027;C;JO59FV;479;N;N;N;  
 950318;1746;SM5BSZ;2;55A;020;57A;029;C;JO89IJ;480;N;N;N;  
 950318;1800;SK5BN;2;51A;021;55A;026;C;JP80UE;585;N;N;N;  
 950318;1820;DL9LBA;2;529;022;559;056;C;JO44UP;213;N;N;N;  
 950318;1830;SK6NP;2;559;023;539;029;B;JO68MB;262;N;N;N;  
 950318;1836;OH1MDR;2;52A;024;57A;023;C;KP01VJ;830;N;N;N;  
 950318;1839;OY9JD;2;51A;025;52A;011;C;IP62OA;1302;N;N;N;  
 950318;1846;OZ9SIG;2;599;026;599;006;B;JO65ER;0;N;N;D